



5217AB/2 Expansion Module

The 5217AB/2 General Input/Output Expansion Module is designed to fit into the Expansion Connector on the 5200CU/2 Controller. Up to 3 General Input/Output Expansion Modules can be installed in a single Clipsal HomeMinder Controller, or 2 Expansion Modules when a Telephone Module is fitted.

The 5217AB/2 provides the user with 8 general outputs and 16 general inputs*. The general inputs can be configured as digital, voltage, current or protected loop inputs and are determined through software configuration.

The general outputs consist of changeover relays normally open (N.O.) and normally closed (N.C.) relay contacts. The maximum rated output voltage is 24V d.c. or 60V a.c. at 1 amp. per output (resistive). With each output is associated a Status Light Emitting Diode (LED).

Features

The Expansion Card may be used to interface to any standard transducer, such as temperature and moisture sensors with voltage or current outputs compatible with the equipment.

Digital inputs such as voltage free switches and movement sensors may also be interfaced to the Expansion Card as part of a security system.

The Expansion Card supports up to 16 inputs (8 general inputs and 8 digital outputs, the setup which is configurable through the installation software).

The 8 general outputs consist of 8 changeover relays (N.O./N.C.) and are used to switch low power applications such as solenoids and strobes. The relay contact is rated at 1A at 24Vdc or 60Vac.

* Version 3.0.8 or higher software is required for this feature, when lower versions of software are used only 8 general inputs are available.



Inputs	<p>8 general purpose inputs, each of which input can be configured as:</p> <ul style="list-style-type: none"> - Protected security loop with double 3.3k EOL - 0 - 1V analogue input - 0 - 10V input - 0 - 30V input - 4 - 20mA current loop input - Temperature sensor input <p>8 digital inputs</p>
Accuracy	The accuracy of the analogue inputs is better than 5%
Outputs	8 SPDT (single pole double throw) relay contact closures (max. load 1A at 24V dc. or 60V ac., resistive)

Technical Specifications

Current	200mA with no loads connected but all output relays energised. (Battery Backed)	
Operating Temperature	0 - 45°C	
Standards	EN50082-1:1992 AS/NZ3548:1995 IEC/CISPR 22:1993 EN55022:1995 89/336/EEC	EMC generic immunity standards Part 1: Residential, commercial and light industry. Conducted and radiated emissions tests.

Note: Clipsal Integrated Systems Pty Ltd reserves the right to change specifications or designs described in this brochure without notice and without obligation.

This product range is part of the  **CLIPSAL HMS**
Home Management Series



CLIPSAL HOME MINDER - The World's Smartest Housekeeper

For further information contact your local Clipsal Office or an accredited Clipsal HomeMinder Installer

Clipsal Integrated Systems Pty Ltd
ACN 089 444 931

Head Office
12 Park Terrace, Bowden
South Australia 5007

PO Box 103, Hindmarsh
South Australia 5007
Telephone (08) 8269 0560
International +61 8 8269 0560
Facsimile (08) 8346 0845
International +61 8 8346 0845
E-Mail cis@clipsal.com.au

Offices in all States

NSW	Sydney	(02) 9794 9200
	Albury	(02) 6041 2377
VIC	Melbourne	(03) 9207 3200
	Country Areas	1800 653 893
QLD	Brisbane	(07) 3244 7444
	Townsville	(07) 4729 3333
SA	Adelaide	(08) 8269 0555
WA	Perth	(08) 9442 4444
TAS	Hobart	(03) 6272 3177
	Launceston	(03) 6331 6951
NT	Darwin	(08) 8947 0278

International Enquiries

Head Office Export Department
Telephone +61 8 8269 0587
Facsimile +61 8 8340 7350
E-Mail export@clipsal.com.au

New Zealand

Clipsal Industries (NZ) Ltd
Auckland
Telephone (09) 576 3403
Facsimile (09) 576 1015
E-Mail headoffice@clipsal.co.nz

Customer Service - North Island

Telephone (09) 572 0014
Free Fax 0800 733 567

Customer Service - South Island

Telephone (03) 379 5368
Free Fax 0800 250 305

clipsal.com